

Product Info

Aerials | Dishes | Mast amplifiers | Mast combiners | Single channel filters | Notch filters | Stacking combiners | Passives | Mounting accessories

Triax MFC series High-performance masthead combiners

MFC 130 - UHF/VHF
Art No. 340130

MFC 140 - UHF/BIII/AM-BII
Art No. 340140

MFC 150 - UHF/UHF
Art No. 340150



MFC130

MFC140

Triax has devoted considerable resources to develop a comprehensive range of masthead combiners, which combines low insertion loss with high out of band rejection.

Choose the one that fits your aerial installation, if you want an easy-to-install signal combiner.

The mast housing has an attractive up-to-date design, in a neutral anthracite colour. The plastic material provides long lasting protection against UV-degradation.

MFC range of masthead combiners with F-connector

- ✓ F-connectors on all in- and outputs
- ✓ Flip and lock mechanism for easy installation
- ✓ Neoprene soft cable grip
- ✓ Attractive design - improved weatherproof housing
- ✓ Low insertion loss



- ✓ High out of band rejection
- ✓ Fully screened enclosure
- ✓ Excellent isolation
- ✓ Switchable through power
- ✓ Field proven mast securing methods - releasable mast strap



Technical data

Type		MFC 130	MFC 140	MFC 150
Art. No.		340130	340140	340150
Input 1	Band	UHF	UHF	UHF
	Channel	21-69	21-69	21-69
	Through loss dB	1.0	1.0	4.5
Input 2	Band	VHF	BIII	UHF
	Channel	2-12	2-12	21-69
	Through loss dB	1.0	1.0	4.5
Input 3	Band		AM-BII	
	Channel		2.5-108 MHz	
	Through loss dB		3.5/1.0	
Stop band attenuation	VHF/BI	dB	> 16	> 20
	FM	dB		> 25
	BIII/DAB	dB		
	UHF	dB	> 16	> 20
	SAT	dB		> 20/> 20
Numbers of in-/output		2/1	3/1	3/1
DC throughpower		5-24V (switchable)	UHF 5-24V	UHF 5-24V
Connector		F-con	F-con	F-con
Weight	kg	0.205	0.265	0.265
Dimensions	Height	mm	115	115
	Depth	mm	60	60
	Width	mm	117	117
Remarks		Throughpower both outputs		



TRIAX A/S

Bjørnkærvej 3 • DK-8783 Hornsyld
+45 76 82 22 00 • +45 75 68 79 66
mail: triax@triax.dk • www.triax.com

